




Decoding the BiSS information

The E201-9S interrogates a BiSS-C encoder and allows the data to be read by a PC using simple ASCII commands over a USB connection and a virtual COM port. Features of the BiSS data transmission and data packet details are described in this document.

BiSS-C timing diagram



MA line is idle high. Communication is initiated with first falling edge. The encoder responds by setting SLO low on the second rising edge on MA. When the encoder is ready for the next request cycle it indicates this to the master by setting SLO high. The absolute position and CRC data is in binary format and sent MSB first.

Encoder reading is started with sending the ASCII character "4" to the E201-9S interface. No CR character is required after the command.

E201-9S returns 16 character hexadecimal string + CR comprising 64 SLO bits synchronized to 64 MA clocks.

Note: Available in E201 interface version 1.16 (and later).

Data packet (containing position, status and CRC) starts right after the "010" sequence (ACK, Start, CDS).

If the ACK sequence is too long and the data packet falls out of the 64-bit word read by the E201-9S the MA clock frequency must be reduced.

E201-9S does not make the line-delay compensation, therefore it is possible that at some setting of the MA clock frequency the readout data is not stable and produces CRC errors. In such case choose different MA clock setting.

For MA clock setting see the "M" command in the E201 data sheet (E201D01).

Recommended clock frequencies for Renishaw Resolute encoders are 280 and 560 kHz.

Example 1

Encoder used in example 1:

Type: Linear absolute encoder, BiSS output

Resolution: 0.05 µm Position length: 32 bits

Status length: 2 bits (active low)

CRC length: 6 bits, polynomial $x^6 + x^1 + 1$ (Represented also as 0x43), inverted

Example of the response to the "4" command: c0040030320ffac0 (hex)

Response										Format						
С	0	0	4	0	0	3	0	3	2	0	F	F	Α	С	0	Hex
1100	0000	0000	0100	0000	0000	0011	0000	0011	0010	0000	1111	1111	1010	1100	0000	Binary

Decoding the response into Position, Status and CRC:

First two bits are always "1"
1100 0000 0000 0100 0000 0011 0000 0011 0010 0000 1111 1111 1010 1100 0000

Next "0" bits are the ACK bits.

Number of ACK bits depends on encoder's latency and BiSS frequency.

1100 0000 0000 0100 0000 0011 0000 0011 0010 0000 1111 1111 1010 1100 0000 ACK

Start bit is always "1"
1100 0000 0000 0100 0000 0011 0000 0011 0010 0000 1111 1111 1010 1100 0000 Start Bit

CDS bit is always "0"
1100 0000 0000 0100 0000 0011 0000 0011 0010 0000 1111 1111 1010 1100 0000 CDS

32 bits of POSITION = 0x00181907 = 1579271 counts
1100 0000 0000 0100 0000 0001 0000 0011 0010 0000 1111 1111 1010 1100 0000 POSITION

2 STATUS bits = 0x03
1100 0000 0100 0000 0000 0011 0000 0011 0010 0000 1111 1111 1010 1100 0000 STATUS

6 CRC bits = 0x3D
1100 0000 0000 0100 0000 0011 0000 0011 0010 0000 1111 1111 1010 1100 0000 CRC

| Ignored bits | 1100 0000 0000 0100 0000 0011 0000 0011 0010 0000 1111 1111 1010 1100 0000 | Ignored |

Calculated encoder position = 1579271 counts × $0.05 \mu m$ = $78963.55 \mu m$ = 78.96355 mm Status bits are 11. As they are active low, encoder operation is correct (no error, no warning).



Example 2

```
Encoder used in example 2:
```

```
Type: Linear absolute encoder, BiSS output Resolution: 1 \mum Position length: 26 bits Status length: 2 bits (active low) CRC length: 6 bits, polynomial x^6 + x^1 + 1 (Represented also as 0x43), inverted Response to the "4" command: c004c9ba71753000 (hex) is decoded as: Position = 0x19374E2 (26440930 decimal) = 26.44093 mm Status = 0x03 (11 binary) = no error, no warning CRC = 0x2A
```

6-bit CRC calculation with 0x43 polynome for BiSS

BiSS communication offers a CRC value to check the correctness of the data read from the encoder. This chapter gives an example of the CRC calculation on the receiver side. The CRC calculation must always be done over the complete set of data. The polynomial for the CRC calculation is $P(x) = x^6 + x^1 + 1$, also represented as 0x43. Following code example must be modified to fit actual data length. Position data, error and warning bits must all be included into calculation in the same order as in the BiSS data packet. ACK, Start and CDS bits are not included in the CRC calculation.

Code example:

```
u8 tableCRC6[64] = {}
                     0x00, 0x03, 0x06, 0x05, 0x0C, 0x0F, 0x0A, 0x09,
                     0x18, 0x1B, 0x1E, 0x1D, 0x14, 0x17, 0x12, 0x11,
                     0x30, 0x33, 0x36, 0x35, 0x3C, 0x3F, 0x3A, 0x39,
                     0x28, 0x2B, 0x2E, 0x2D, 0x24, 0x27, 0x22, 0x21,
                     0x23, 0x20, 0x25, 0x26, 0x2F, 0x2C, 0x29, 0x2A,
                     0x3B, 0x38, 0x3D, 0x3E, 0x37, 0x34, 0x31, 0x32,
                     0x13, 0x10, 0x15, 0x16, 0x1F, 0x1C, 0x19, 0x1A,
                     0x0B, 0x08, 0x0D, 0x0E, 0x07, 0x04, 0x01, 0x02};
u8 crcBiSS(u32 data)
  {
       u8 crc;
       u32 tmp
       tmp = (data >> 30) & 0x00000003;
       crc = ((data >> 24) & 0x0000003F);
       tmp = crc ^ tableCRC6[tmp];
       crc = ((data >> 18) & 0x0000003F);
       tmp = crc ^ tableCRC6[tmp];
       crc = ((data >> 12) & 0x0000003F);
       tmp = crc ^ tableCRC6[tmp];
       crc = ((data >> 6) \& 0x0000003F);
       tmp = crc ^ tableCRC6[tmp];
       crc = (data \& 0x0000003F);
       tmp = crc ^ tableCRC6[tmp];
       crc = tableCRC6[tmp];
       return crc;
  }
```

Recommended literature:

- Painless guide to CRC error detection algorithm; Ross N. Williams.
- Cyclic Redundancy Code (CRC) Polynomial Selection For Embedded Networks; P. Koopman, T. Chakravarty
- Data sheet L-9709-9005 BiSS C-mode (undirectional) for Resolute encoders: http://www.renishaw.com/en/



Head office

RLS merilna tehnika d.o.o.

Poslovna cona Žeje pri Komendi Pod vrbami 2 SI-1218 Komenda Slovenia

T +386 1 5272100 F +386 1 5272129 E mail@rls.si www.rls.si

Document issues

Issue	Date	Page	Corrections made	
1	24. 8. 2015	-	New document	
2	9. 2. 2017	1	BiSS-C timing diagram amended	
		3	6-bit CRC calculation description amended	

This product is not designed or intended for use outside the environmental limitations and operating parameters expressly stated on the product's datasheet. Products are not designed or intended for use in medical, military, aerospace, automotive or oil & gas applications or any safety-critical applications where a failure of the product could cause severe environmental or property damage, personal injury or death. Any use in such applications must be specifically agreed to by seller in writing, and is subject to such additional terms as the seller may impose in its sole discretion. Use of products in such applications is at buyer's own risk, and buyer will indemnify and hold harmless seller and its affiliates against any liability, loss, damage or expense arising from such use. Information contained in this datasheet was derived from product testing under controlled laboratory conditions and data reported thereon is subject to the stated tolerances and variations, or if none are stated, then to tolerances and variations consistent with usual trade practices and testing methods. The product's performance outside of laboratory conditions, including when one or more operating parameters is at its maximum range, may not conform to the product's datasheet. Further, information in the product's datasheet does not reflect the performance of the product in any application, end-use or operating environment buyer or its customer may put the product to. Seller and its affiliates make no recommendation, warranty or representation as to the suitability of the product for buyer's application, use, end-product, process or combination with any other product or as to any results buyer or its customer might obtain in their use of the product. Buyer should use its own knowledge, judgment, expertise and testing in selecting the product for buyer's application, end-use and/or operating environment, and should not rely on any oral or written statement, representation, or samples made by seller or its affiliates for any purpose. EXC

RLS merilna tehnika d.o.o. has made considerable effort to ensure the content of this document is correct at the date of publication but makes no warranties or representations regarding the content. RLS merilna tehnika d.o.o. excludes liability, howsoever arising, for any inaccuracies in this document.